


LEDDR500-800D
 20-30W 500-800mA Current
 Adjustable Constant Current Driver



GRC Lighting
R & C Agency International
Lighting Specialists for over 15 years



Description OPTOTRONIC® OSRAM LED Power Supply with high reliability in extra small & compact housing, providing trailing dimming performance. It equips with 4 selectable currents, fits in light fixtures for shop and office lighting. Suitable for use with electronic Trailing Edge dimmer; 4 output current selected by DIP-switch; Low ripple for output current Small housing for compact fixture.

Item Code	Input	Max. Wattage	Output Range	Current	Output Set Via	Dimmable	Flex & Plug	Size L x W x H
LEDDR500-800D	240V	20W 24W 28W 30W	27-40VDC 27-40VDC 27-40VDC 27-37VDC	500mA 600mA 700mA 800mA	Dip-switch	Yes (TRIAC)	No	95 x 53 x 30 mm

R&C AGENCY INTERNATIONAL

94 Wecker Road,
 Mansfield, QLD, 4122

Email: sales@rcagency.com.au
 Ph: (07) 3216 2888
 Fax: (07) 3216 2999

Opening Hour:
 8:00am to 4:30pm Monday to Friday
 *Showroom by appointment only